


1. MAC Address Setting : Not Display

Softphone version 4.2 does **not display MAC setting**.

<Softphone>



<PBX Web-MC>

Status	IP Phone Registration ID (MAC Address)
ALL	
Registered	00:80:F0:92:8D:71
Registered	00:80:F0:92:9E:D1
None	00:00:00:00:00:00

Q : Which MAC address should be registered to PBX for IP phone registration ID, if PBX installer wants to register it manually?

A : **One of any MAC addresses** on a PC can be used.

Therefore **even before installing the softphone application** on a PC, end users can notify the PBX installer of **one of any MAC addresses**. DOS command : >ipconfig/all

Softphone version 4.2 sends all MAC addresses until the PBX responds.

2. MAC Address Setting : Note

Q : When the **MAC address of wired LAN** is registered to PBX, can softphone communicate with PBX using **Wi-Fi**?

A : Yes. IP softphone sends the registered MAC to PBX always regardless of connection method (Wired, Wi-Fi or others).

Note :

Softphone version 4.1 or before also uses programmed MAC always. But some PC hides MAC address of Wired LAN from the application during Wi-Fi is used.

Softphone version 4.2 improved for this PC and for easy installation as previous page.

3. MAC Address Setting : If Want to Change

Q : If we want to change MAC setting, what should we do?

A : Solution is as follows.

1. Register new MAC address to PBX by WebMC.
2. Uninstall softphone application and install it again.